

































November 2015







# HEARING INSTRUMENT OVERVIEW

**bernafon**<sup>®</sup>  
Your hearing · Our passion





	1	3	5	7	9
	NEVARA 1 INIZIA 1	SAPHIRA 3 SUPREMIA 3 CARISTA 3 INIZIA 3	SAPHIRA 5 CARISTA 5 CHRONOS 5	JUNA 7 SUPREMIA 7 ACRIVA 7 CHRONOS 7	JUNA 9 ACRIVA 9 CHRONOS 9
	Ability to perceive sounds naturally.				
	Ability to focus on speech understanding in challenging hearing situations.				
	Ability to provide wearing comfort in a wide range of noisy environments.				
	Ability to provide easy use and handling in changing listening environments.				
	Ability to configure the hearing system according to the users' needs and preferences.				
	Ability to connect the hearing system to mobile phones and other electronic devices wirelessly.				

## BENEFITS

	Ability to perceive sounds naturally.
	Ability to focus on speech understanding in challenging hearing situations.
	Ability to provide wearing comfort in a wide range of noisy environments.
	Ability to provide easy use and handling in changing listening environments.
	Ability to configure the hearing system according to the users' needs and preferences.
	Ability to connect the hearing system to mobile phones and other electronic devices wirelessly.

## FEATURES

ChannelFree™					
Speech Cue Priority					
Bandwidth	8 kHz	8 kHz	8 kHz	10 kHz	10 kHz
Frequency Composition™	-				
Adaptive Noise Reduction Plus					
Adaptive Feedback Canceller Plus					
Transient Noise Reduction	-	-			
Binaural Synchronization of VC, Program, Mute					
Binaural Coordination	-	-	-		
Environment Optimizer	-	-	-		
Wind Noise Monitor	-				
Reverb Reduction	-	-	-	-	
i-VC	-	-	-		
Data Logging					
Data Learning	-	-			
Language Specific Targets					
Adaptive Directionality	-				
Automatic Directionality		-	-	-	-
High-Frequency Directionality	-	-	-	-	
True Directionality™	-	-	-	-	
Live Music and Cinema Programs	-	-			
Comfort in Airplane Program	-	-	-	-	
Remote Control (optional)					
Connectivity Accessories (optional)	-				



## CHRONOS 9

	Gain / MPO				Parameters																Options			User Controls								
	Gain Max (dB) – Ear sim.	Max Out (dB SPL) – Ear sim.	Gain Max (dB) – 2cc	Max Out (dB SPL) – 2cc	Battery Size	ChannelFree™	Speech Cue Priority™	Frequency Composition™	Bandwidth (kHz)	Binaural Synchronization	Adaptive Directionality	True Directionality™	Automatic Directionality	Adaptive Noise Reduction Plus	Transient Noise Reduction	Reverb Reduction	Soft Noise Management	Wind Noise Monitor	Adap. Feedback Canceller Plus	Intelligent VC	Smart VC	Program Memories/Options	Environment Optimizer	Data Logging/Data Learning	Live Music/Cinema Programs	Comfort in Airplane Program	Thin Tube 0.9/1.3 mm	Telecoil/Auto Telephone	FM/DAI Adapter	Program Sel./Volume Control	Remote Control RC-N	Connectivity Accessories
<b>BTE</b>																																
CN9 CPx	75	138	71	133	13	●	-	-	10	●	-	-	-	-	●	-	■	-	●	-	●	4/13	■	●/●	●/●	-	●	●/●	o/o	●/●	o	o
CN9 CP	66	134	61	127	13	●	-	-	10	●	■	-	-	-	●	-	■	-	●	-	●	4/13	■	●/●	●/●	-	●	●/●	o/o	●/●	o	o
CN9 M	62	126	51	115	312	●	-	-	10	●	■	-	-	-	●	-	■	-	●	-	●	4/13	■	●/●	●/●	-	●	●/●	o/o	●/●	o	o
CN9 N	55	127	50	121	312	●	-	-	10	●	■	-	-	-	●	-	■	-	●	-	●	4/11	■	●/●	●/●	-	●	-	-	●/● <sup>1</sup>	o	o
<b>RITE</b>																																
CN9 NR	73	132	63	123	312	●	-	-	10	●	■	-	-	-	●	-	■	-	●	-	●	4/12	■	●/●	●/●	-	●	●/●	-	●/● <sup>1</sup>	o	o
<b>ITE</b>																																
CN9 ITED	65	133	57	124	13	●	-	-	10	-	■	-	-	-	●	-	■	-	●	-	●	4/10	■	●/●	●/●	-	o/o	-	o/o	-	-	
CN9 ITCPD	62	129	53	119	312	●	-	-	10	-	■	-	-	-	●	-	■	-	●	-	●	4/10	■	●/●	●/●	-	o/o	-	o/o	-	-	
CN9 ITCD	56	123	46	113	312	●	-	-	10	●	■	-	-	-	●	-	■	-	●	-	●	4/12	■	●/●	●/●	-	o/o	-	o/o	o	o	
CN9 ITCP	63	130	53	119	312	●	-	-	10	-	-	-	-	-	●	-	■	-	●	-	●	4/10	■	●/●	●/●	-	o/o	-	o/o	-	-	
CN9 CICP	61	129	50	118	10	●	-	-	10	-	-	-	-	-	●	-	■	-	●	-	-	1/9	■	●/-	●/●	-	-	-	-	-	-	
CN9 CIC	49	118	39	109	10	●	-	-	10	-	-	-	-	-	●	-	■	-	●	-	-	1/9	■	●/-	●/●	-	-	-	-	-	-	

## JUNA 7

	Gain / MPO				Parameters																Options			User Controls								
	Gain Max (dB) – Ear sim.	Max Out (dB SPL) – Ear sim.	Gain Max (dB) – 2cc	Max Out (dB SPL) – 2cc	Battery Size	ChannelFree™	Speech Cue Priority™	Frequency Composition™	Bandwidth (kHz)	Binaural Synchronization	Adaptive Directionality	True Directionality™	Automatic Directionality	Adaptive Noise Reduction Plus	Transient Noise Reduction	Reverb Reduction	Soft Noise Management	Wind Noise Monitor	Adap. Feedback Canceller Plus	Intelligent VC	Smart VC	Program Memories/Options	Environment Optimizer	Data Logging/Data Learning	Live Music/Cinema Programs	Comfort in Airplane Program	Thin Tube 0.9/1.3 mm	Telecoil/Auto Telephone	FM/DAI Adapter	Program Sel./Volume Control	Remote Control RC-N	Connectivity Accessories
<b>BTE</b>																																
JU7 CPx	77	138	71	132	13	●	●	●	10	●	-	-	-	■	●	-	■	-	●	●	●	4/15	■	●/●	●/●	-	●	●/●	o/o	●/●	o	o
JU7 CP	68	135	62	128	13	●	●	●	10	●	■	-	-	■	●	-	■	-	●	●	●	4/15	■	●/●	●/●	-	●	●/●	o/o	●/●	o	o
JU7 P	72	138	68	134	13	●	●	●	10	●	■	-	-	■	●	-	■	-	●	●	●	4/15	■	●/●	●/●	-	●	●/●	o/o	●/●	o	o
JU7 N	55	127	48	122	312	●	●	●	10	●	■	-	-	■	●	-	■	-	●	●	●	4/12	■	●/●	●/●	-	●	-	-	●/● <sup>1</sup>	o	o
<b>RITE</b>																																
JU7 PR	73	132	65	123	312	●	●	●	10	●	■	-	-	■	●	-	■	-	●	●	●	4/13	■	●/●	●/●	-	-	-	●/● <sup>1</sup>	o	o	
JU7 NR	75	133	65	124	312	●	●	●	10	●	■	-	-	■	●	-	■	-	●	●	●	4/14	■	●/●	●/●	-	-	●/●	-	●/● <sup>1</sup>	o	o
<b>ITE</b>																																
JU7 ITEPD	70	135	63	127	13	●	●	●	10	●	■	-	-	■	●	-	■	-	●	●	●	4/14	■	●/●	●/●	-	o/o	-	o/o <sup>1</sup>	o	o	
JU7 ITED	61	130	52	121	13	●	●	●	10	●	■	-	-	■	●	-	■	-	●	●	●	4/14	■	●/●	●/●	-	o/o	-	o/o <sup>1</sup>	o	o	
JU7 ITCPD	70	135	63	127	312	●	●	●	10	●	■	-	-	■	●	-	■	-	●	●	●	4/14	■	●/●	●/●	-	o/o	-	o/o <sup>1</sup>	o	o	
JU7 ITCD	59	128	50	117	312	●	●	●	10	●	■	-	-	■	●	-	■	-	●	●	●	4/14	■	●/●	●/●	-	o/o	-	o/o <sup>1</sup>	o	o	
JU7 ITC	59	128	50	117	312	●	●	●	10	-	-	-	-	■	●	-	■	-	●	●	●	4/11	■	●/●	●/●	-	o/o	-	o/o	-	-	
JU7 CICP	58	126	48	117	10	●	●	●	10	●	-	-	-	■	●	-	■	-	●	●	●	4/12	■	●/●	●/●	-	-	-	-	o/o <sup>1</sup>	o	o
JU7 CICx	53	119	43	109	10	●	●	●	10	●	-	-	-	■	●	-	■	-	●	●	●	4/12	■	●/●	●/●	-	-	-	-	o/o <sup>1</sup>	o	o
JU7 CIC	52	120	42	109	10	●	●	●	10	-	-	-	-	■	●	-	■	-	●	●	●	4/9	■	●/-	●/●	-	-	-	-	o/-	-	-

<sup>1</sup> Program selector can be configured as a volume control

## ACRIVA 7

	Gain / MPO				Parameters																Options			User Controls								
	Gain Max (dB) – Ear sim.	Max Out (dB SPL) – Ear sim.	Gain Max (dB) – 2cc	Max Out (dB SPL) – 2cc	Battery Size	ChannelFree™	Speech Cue Priority™	Frequency Composition™	Bandwidth (kHz)	Binaural Synchronization	Adaptive Directionality	True Directionality™	Automatic Directionality	Adaptive Noise Reduction Plus	Transient Noise Reduction	Reverb Reduction	Soft Noise Management	Wind Noise Monitor	Adap. Feedback Canceller Plus	Intelligent VC	Smart VC	Program Memories/Options	Environment Optimizer	Data Logging/Data Learning	Live Music/Cinema Programs	Comfort in Airplane Program	Thin Tube 0.9/1.3 mm	Telecoil/Auto Telephone	FM/DAI Adapter	Program Sel./Volume Control	Remote Control RC-N	Connectivity Accessories
<b>BTE</b>																																
AR7 CPx	77	138	71	132	13	●	-	●	10	●	-	-	-	●	-	●	-	-	●	-	-	4/11	●	●/●	-	-	●	●/●	o/o	●/●	o	o
AR7 CP	67	134	61	128	13	●	-	●	10	●	●	-	-	●	-	●	-	-	●	-	-	4/11	●	●/●	-	-	●	●/●	o/o	●/●	o	o
AR7 N	54	128	48	122	312	●	-	●	10	●	●	-	-	●	-	●	-	-	●	-	-	4/9	●	●/●	-	-	●	-	●/● <sup>1</sup>	o	o	
<b>RITE</b>																																
AR7 NR	74	133	64	124	312	●	-	●	10	●	●	-	-	●	-	●	-	-	●	-	-	4/10	●	●/●	-	-	●	-	●/● <sup>1</sup>	o	o	
<b>ITE</b>																																
AR7 ITED	60	130	51	120	13	●	-	●	10	●	●	-	-	●	-	●	-	-	●	-	-	4/10	●	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o	
AR7 ITCPD	61	129	52	119	312	●	-	●	10	●	●	-	-	●	-	●	-	-	●	-	-	4/10	●	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o	
AR7 ITCD	59	128	50	117	312	●	-	●	10	●	●	-	-	●	-	●	-	-	●	-	-	4/10	●	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o	
AR7 ITC	59	128	50	117	312	●	-	●	10	-	-	-	-	●	-	●	-	-	●	-	-	4/8	●	●/●	-	-	o/o	-	o/o	-	-	
AR7 CICP	59	127	48	116	10	●	-	●	10	-	-	-	-	●	-	●	-	-	●	-	-	4/7	●	●/-	-	-	-	-	o/-	-	-	
AR7 CIC	51	119	42	109	10	●	-	●	10	-	-	-	-	●	-	●	-	-	●	-	-	4/7	●	●/-	-	-	-	-	o/-	-	-	

## CHRONOS 7

	Gain / MPO				Parameters																Options			User Controls								
	Gain Max (dB) – Ear sim.	Max Out (dB SPL) – Ear sim.	Gain Max (dB) – 2cc	Max Out (dB SPL) – 2cc	Battery Size	ChannelFree™	Speech Cue Priority™	Frequency Composition™	Bandwidth (kHz)	Binaural Synchronization	Adaptive Directionality	True Directionality™	Automatic Directionality	Adaptive Noise Reduction Plus	Transient Noise Reduction	Reverb Reduction	Soft Noise Management	Wind Noise Monitor	Adap. Feedback Canceller Plus	Intelligent VC	Smart VC	Program Memories/Options	Environment Optimizer	Data Logging/Data Learning	Live Music/Cinema Programs	Comfort in Airplane Program	Thin Tube 0.9/1.3 mm	Telecoil/Auto Telephone	FM/DAI Adapter	Program Sel./Volume Control	Remote Control RC-N	Connectivity Accessories
<b>BTE</b>																																
CN7 CPx	75	138	71	133	13	●	-	-	10	●	-	-	-	●	-	●	-	-	●	-	-	4/11	●	●/●	-	-	●	●/●	o/o	●/●	o	o
CN7 CP	66	134	61	127	13	●	-	-	10	●	●	-	-	●	-	●	-	-	●	-	-	4/11	●	●/●	-	-	●	●/●	o/o	●/●	o	o
CN7 M	62	126	51	115	312	●	-	-	10	●	●	-	-	●	-	●	-	-	●	-	-	4/11	●	●/●	-	-	●	●/●	o/o	●/●	o	o
CN7 N	55	127	50	121	312	●	-	-	10	●	●	-	-	●	-	●	-	-	●	-	-	4/9	●	●/●	-	-	●	-	●/● <sup>1</sup>	o	o	
<b>RITE</b>																																
CN7 NR	73	132	63	123	312	●	-	-	10	●	●	-	-	●	-	●	-	-	●	-	-	4/10	●	●/●	-	-	●	-	●/● <sup>1</sup>	o	o	
<b>ITE</b>																																
CN7 ITED	65	133	57	124	13	●	-	-	10	-	●	-	-	●	-	●	-	-	●	-	-	4/8	●	●/●	-	-	o/o	-	o/o	-	-	
CN7 ITCPD	62	129	53	119	312	●	-	-	10	-	●	-	-	●	-	●	-	-	●	-	-	4/8	●	●/●	-	-	o/o	-	o/o	-	-	
CN7 ITCD	56	123	46	113	312	●	-	-	10	●	●	-	-	●	-	●	-	-	●	-	-	4/10	●	●/●	-	-	o/o	-	o/o	o	o	
CN7 ITCP	63	130	53	119	312	●	-	-	10	-	-	-	-	●	-	●	-	-	●	-	-	4/8	●	●/●	-	-	o/o	-	o/o	-	-	
CN7 CICP	61	129	50	118	10	●	-	-	10	-	-	-	-	●	-	●	-	-	●	-	-	1/7	●	●/-	-	-	-	-	-	-	-	
CN7 CIC	49	118	39	109	10	●	-	-	10	-	-	-	-	●	-	●	-	-	●	-	-	1/7	●	●/-	-	-	-	-	-	-	-	

<sup>1</sup> Program selector can be configured as a volume control

	Gain / MPO				Parameters																Options			User Controls							
	Gain Max (dB) – Ear sim.	Max Out (dB SPL) – Ear sim.	Gain Max (dB) – 2cc	Max Out (dB SPL) – 2cc	Battery Size	ChannelFree™	Speech Cue Priority™	Frequency Composition™	Bandwidth (kHz)	Binaural Synchronization	Adaptive Directionality	True Directionality™	Automatic Directionality	Adaptive Noise Reduction Plus	Transient Noise Reduction	Reverb Reduction	Soft Noise Management	Wind Noise Monitor	Adap. Feedback Canceller Plus	Intelligent VC	Smart VC	Program Memories/Options	Environment Optimizer	Data Logging/Data Learning	Live Music/Cinema Programs	Comfort in Airplane Program	Thin Tube 0.9/1.3 mm	Telecoil/Auto Telephone	FM/DAI Adapter	Program Sel./Volume Control	Remote Control RC-N

## SAPHIRA 5

<b>BTE</b>																																		
SA5 CPx	77	137	71	132	13	●	●	●	8	●	-	-	-	●	●	-	●	●	-	-	-	4/15	-	●/●	●/●	-	●	●/●	o/o	●/●	o	o		
SA5 CP	67	134	61	128	13	●	●	●	8	●	●	-	-	●	●	-	●	●	-	-	-	4/15	-	●/●	●/●	-	●	●/●	o/o	●/●	o	o		
SA5 P	72	138	68	134	13	●	●	●	8	●	●	-	-	●	●	-	●	●	-	-	-	4/15	-	●/●	●/●	-	●	●/●	o/o	●/●	o	o		
SA5 N	55	128	49	122	312	●	●	●	8	●	●	-	-	●	●	-	●	●	-	-	-	4/12	-	●/●	●/●	-	●	-	●/● <sup>1</sup>	o	o			
<b>RITE</b>																																		
SA5 PR	73	131	64	123	312	●	●	●	8	●	●	-	-	●	●	-	●	●	-	-	-	4/13	-	●/●	●/●	-	-	●/●	-	●/● <sup>1</sup>	o	o		
SA5 NR	73	132	64	123	312	●	●	●	8	●	●	-	-	●	●	-	●	●	-	-	-	4/14	-	●/●	●/●	-	-	●/●	-	●/● <sup>1</sup>	o	o		
<b>ITE</b>																																		
SA5 ITEPD	69	134	62	126	13	●	●	●	8	●	●	-	-	●	●	-	●	●	-	-	-	4/14	-	●/●	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o		
SA5 ITED	60	129	51	121	13	●	●	●	8	●	●	-	-	●	●	-	●	●	-	-	-	4/14	-	●/●	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o		
SA5 ITCPD	69	134	62	126	312	●	●	●	8	●	●	-	-	●	●	-	●	●	-	-	-	4/14	-	●/●	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o		
SA5 ITCD	60	128	50	118	312	●	●	●	8	●	●	-	-	●	●	-	●	●	-	-	-	4/14	-	●/●	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o		
SA5 ITC	60	128	50	118	312	●	●	●	8	-	-	-	-	●	●	-	●	●	-	-	-	4/11	-	●/●	●/●	-	-	o/o	-	o/o	-	-		
SA5 CICP	57	125	47	116	10	●	●	●	8	●	-	-	-	●	●	-	●	●	-	-	-	4/12	-	●/●	●/●	-	-	-	-	o/o <sup>1</sup>	o	o		
SA5 CICx	52	119	42	109	10	●	●	●	8	●	-	-	-	●	●	-	●	●	-	-	-	4/12	-	●/●	●/●	-	-	-	-	o/o <sup>1</sup>	o	o		
SA5 CIC	51	118	41	108	10	●	●	●	8	-	-	-	-	●	●	-	●	●	-	-	-	4/9	-	●/●	●/●	-	-	-	-	-	-	-		
SA5 IIC	46	119	35	109	10	●	●	●	8	-	-	-	-	●	●	-	●	●	-	-	-	1/9	-	●/●	●/●	-	-	-	-	-	-	-		

## CARISTA 5

<b>BTE</b>																																		
CA5 CPx	77	137	71	132	13	●	-	-	8	●	-	-	-	●	●	-	●	●	-	-	-	4/12	-	●/●	-	-	●	●/●	o/o	●/●	o	o		
CA5 CP	67	134	61	128	13	●	-	-	8	●	●	-	-	●	●	-	●	●	-	-	-	4/12	-	●/●	-	-	●	●/●	o/o	●/●	o	o		
CA5 N	55	128	49	122	312	●	-	-	8	●	●	-	-	●	●	-	●	●	-	-	-	4/9	-	●/●	-	-	●	-	●/● <sup>1</sup>	o	o			
<b>RITE</b>																																		
CA5 NR	73	132	64	123	312	●	-	-	8	●	●	-	-	●	●	-	●	●	-	-	-	4/11	-	●/●	-	-	●	-	●/● <sup>1</sup>	o	o			
<b>ITE</b>																																		
CA5 ITED	61	130	52	120	13	●	-	-	8	●	●	-	-	●	●	-	●	●	-	-	-	4/11	-	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o			
CA5 ITCPD	62	129	53	120	312	●	-	-	8	●	●	-	-	●	●	-	●	●	-	-	-	4/11	-	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o			
CA5 ITCD	60	128	50	118	312	●	-	-	8	●	●	-	-	●	●	-	●	●	-	-	-	4/11	-	●/●	-	-	o/o	-	o/o <sup>1</sup>	o	o			
CA5 ITC	60	128	50	118	312	●	-	-	8	-	-	-	-	●	●	-	●	●	-	-	-	4/9	-	●/●	-	-	o/o	-	o/o	-	-			
CA5 CICP	57	125	48	117	10	●	-	-	8	●	-	-	-	●	●	-	●	●	-	-	-	4/7	-	●/●	-	-	-	-	o/o	-	-			
CA5 CIC	51	118	41	108	10	●	-	-	8	-	-	-	-	●	●	-	●	●	-	-	-	4/7	-	●/●	-	-	-	-	o/o	-	-			

<sup>1</sup> Program selector can be configured as a volume control

## CHRONOS 5

	Gain / MPO				Parameters																Options			User Controls								
	Gain Max (dB) – Ear sim.	Max Out (dB SPL) – Ear sim.	Gain Max (dB) – 2cc	Max Out (dB SPL) – 2cc	Battery Size	ChannelFree™	Speech Cue Priority™	Frequency Composition™	Bandwidth (kHz)	Binaural Synchronization	Adaptive Directionality	True Directionality™	Automatic Directionality	Adaptive Noise Reduction Plus	Transient Noise Reduction	Reverb Reduction	Soft Noise Management	Wind Noise Monitor	Adap. Feedback Canceller Plus	Intelligent VC	Smart VC	Program Memories/Options	Environment Optimizer	Data Logging/Data Learning	Live Music/Cinema Programs	Comfort in Airplane Program	Thin Tube 0.9/1.3 mm	Telecoil/Auto Telephone	FM/DAI Adapter	Program Sel./Volume Control	Remote Control RC-N	Connectivity Accessories
<b>BTE</b>																																
CN5 CPx	75	138	71	133	13	●	-	-	8	●	-	-	-	-	-	-	■	-	●	-	-	4/11	-	●/-	-	-	●	●/●	o/o	●/●	o	o
CN5 CP	66	134	61	127	13	●	-	-	8	●	■	-	-	-	-	-	■	●	●	-	-	4/11	-	●/-	-	-	●	●/●	o/o	●/●	o	o
CN5 M	62	126	51	115	312	●	-	-	8	●	■	-	-	-	-	-	■	●	●	-	-	4/11	-	●/-	-	-	●	●/●	o/o	●/●	o	o
CN5 N	55	127	50	121	312	●	-	-	8	●	■	-	-	-	-	-	■	●	●	-	-	4/9	-	●/-	-	-	●	-	-	●/● <sup>1</sup>	o	o
<b>RITE</b>																																
CN5 NR	73	132	63	123	312	●	-	-	8	●	■	-	-	-	-	-	■	●	●	-	-	4/10	■	●/-	-	-	●/●	-	●/● <sup>1</sup>	o	o	
<b>ITE</b>																																
CN5 ITED	65	133	57	124	13	●	-	-	8	-	■	-	-	-	-	-	■	●	●	-	-	4/8	■	●/-	-	-	o/o	-	o/o	-	-	
CN5 ITCPD	62	129	53	119	312	●	-	-	8	-	■	-	-	-	-	-	■	●	●	-	-	4/8	■	●/-	-	-	o/o	-	o/o	-	-	
CN5 ITCD	56	123	46	113	312	●	-	-	8	●	■	-	-	-	-	-	■	●	●	-	-	4/10	■	●/-	-	-	o/●	-	o/o	o	o	
CN5 ITCP	63	130	53	119	312	●	-	-	8	-	-	-	-	-	-	-	■	-	●	-	-	4/8	■	●/-	-	-	o/o	-	o/o	-	-	
CN5 CICP	61	129	50	118	10	●	-	-	8	-	-	-	-	-	-	-	■	-	●	-	-	1/7	■	●/-	-	-	-	-	-	-	-	
CN5 CIC	49	118	39	109	10	●	-	-	8	-	-	-	-	-	-	-	■	-	●	-	-	1/7	■	●/-	-	-	-	-	-	-	-	

## SAPHIRA 3

	Gain / MPO				Parameters																Options			User Controls								
	Gain Max (dB) – Ear sim.	Max Out (dB SPL) – Ear sim.	Gain Max (dB) – 2cc	Max Out (dB SPL) – 2cc	Battery Size	ChannelFree™	Speech Cue Priority™	Frequency Composition™	Bandwidth (kHz)	Binaural Synchronization	Adaptive Directionality	True Directionality™	Automatic Directionality	Adaptive Noise Reduction Plus	Transient Noise Reduction	Reverb Reduction	Soft Noise Management	Wind Noise Monitor	Adap. Feedback Canceller Plus	Intelligent VC	Smart VC	Program Memories/Options	Environment Optimizer	Data Logging/Data Learning	Live Music/Cinema Programs	Comfort in Airplane Program	Thin Tube 0.9/1.3 mm	Telecoil/Auto Telephone	FM/DAI Adapter	Program Sel./Volume Control	Remote Control RC-N	Connectivity Accessories
<b>BTE</b>																																
SA3 CPx	77	137	71	132	13	●	●	●	8	●	-	-	-	■	-	-	■	-	●	-	-	4/12	-	●/-	●/-	-	●	●/●	o/o	●/●	o	o
SA3 CP	67	134	61	128	13	●	●	●	8	●	■	-	-	■	-	-	■	●	●	-	-	4/12	-	●/-	●/-	-	●	●/●	o/o	●/●	o	o
SA3 P	72	138	68	134	13	●	●	●	8	●	■	-	-	■	-	-	■	●	●	-	-	4/12	-	●/-	●/-	-	●	●/●	o/o	●/●	o	o
SA3 N	55	128	49	122	312	●	●	●	8	●	■	-	-	■	-	-	■	●	●	-	-	4/9	-	●/-	●/-	-	●	-	-	●/● <sup>1</sup>	o	o
<b>RITE</b>																																
SA3 PR	73	131	64	123	312	●	●	●	8	●	■	-	-	■	-	-	■	●	●	-	-	4/10	-	●/-	●/-	-	-	-/●	-	●/● <sup>1</sup>	o	o
SA3 NR	73	132	64	123	312	●	●	●	8	●	■	-	-	■	-	-	■	●	●	-	-	4/11	-	●/-	●/-	-	-	●/●	-	●/● <sup>1</sup>	o	o
<b>ITE</b>																																
SA3 ITEPD	69	134	62	126	13	●	●	●	8	●	■	-	-	■	-	-	■	●	●	-	-	4/11	-	●/-	●/-	-	-	o/o	-	o/o <sup>1</sup>	o	o
SA3 ITED	60	129	51	121	13	●	●	●	8	●	■	-	-	■	-	-	■	●	●	-	-	4/11	-	●/-	●/-	-	-	o/o	-	o/o <sup>1</sup>	o	o
SA3 ITCPD	69	134	62	126	312	●	●	●	8	●	■	-	-	■	-	-	■	●	●	-	-	4/11	-	●/-	●/-	-	-	o/o	-	o/o <sup>1</sup>	o	o
SA3 ITCD	60	128	50	118	312	●	●	●	8	●	■	-	-	■	-	-	■	●	●	-	-	4/11	-	●/-	●/-	-	-	o/o	-	o/o <sup>1</sup>	o	o
SA3 ITC	60	128	50	118	312	●	●	●	8	-	-	-	-	■	-	-	■	-	●	-	-	4/8	-	●/-	●/-	-	-	o/o	-	o/o	-	-
SA3 CICP	57	125	47	116	10	●	●	●	8	●	-	-	-	■	-	-	■	-	●	-	-	4/9	-	●/-	●/-	-	-	-	-	o/o <sup>1</sup>	o	o
SA3 CICx	52	119	42	109	10	●	●	●	8	●	-	-	-	■	-	-	■	-	●	-	-	4/9	-	●/-	●/-	-	-	-	-	o/o <sup>1</sup>	o	o
SA3 CIC	51	118	41	108	10	●	●	●	8	-	-	-	-	■	-	-	■	-	●	-	-	4/6	-	●/-	●/-	-	-	-	-	-	-	-

<sup>1</sup> Program selector can be configured as a volume control



	Gain / MPO				Parameters																Options			User Controls							
	Gain Max (dB) – Ear sim.	Max Out (dB SPL) – Ear sim.	Gain Max (dB) – 2cc	Max Out (dB SPL) – 2cc	Battery Size	ChannelFree™	Speech Cue Priority™	Frequency Composition™	Bandwidth (kHz)	Binaural Synchronization	Adaptive Directionality	True Directionality™	Automatic Directionality	Adaptive Noise Reduction Plus	Transient Noise Reduction	Reverb Reduction	Soft Noise Management	Wind Noise Monitor	Adap. Feedback Canceller Plus	Intelligent VC	Smart VC	Program Memories/Options	Environment Optimizer	Data Logging/Data Learning	Live Music/Cinema Programs	Comfort in Airplane Program	Thin Tube 0.9/1.3 mm	Telecoil/Auto Telephone	FM/DAI Adapter	Program Sel./Volume Control	Remote Control RC-N

### CARISTA3

<b>BTE</b>																																				
CA3 CPx	77	137	71	132	13	●	-	-	8	●	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
CA3 CP	67	134	61	128	13	●	-	-	8	●	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
CA3 N	55	128	49	122	312	●	-	-	8	●	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
<b>RITE</b>																																				
CA3 NR	73	132	64	123	312	●	-	-	8	●	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
<b>ITE</b>																																				
CA3 ITED	61	130	52	120	13	●	-	-	8	●	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
CA3 ITCPD	62	129	53	120	312	●	-	-	8	●	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
CA3 ITCD	60	128	50	118	312	●	-	-	8	●	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
CA3 ITC	60	128	50	118	312	●	-	-	8	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
CA3 CICP	57	125	48	117	10	●	-	-	8	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
CA3 CIC	51	118	41	108	10	●	-	-	8	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-

### INIZIA 3

<b>BTE</b>																																				
IN3 CPx	75	138	71	133	13	●	-	-	8	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
IN3 CP	66	134	61	127	13	●	-	-	8	-	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
IN3 N	55	127	50	121	312	●	-	-	8	-	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
<b>RITE</b>																																				
IN3 NR	73	132	63	123	312	●	-	-	8	-	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
<b>ITE</b>																																				
IN3 ITED	65	133	57	124	13	●	-	-	8	-	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
IN3 ITCPD	56	123	46	113	312	●	-	-	8	-	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
IN3 ITCD	56	124	45	113	312	●	-	-	8	-	■	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
IN3 ITC	63	130	53	119	312	●	-	-	8	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
IN3 CICP	61	129	50	118	10	●	-	-	8	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
IN3 CIC	49	118	39	109	10	●	-	-	8	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-

<sup>1</sup> Program selector can be configured as a volume control

	Gain /MPO				Parameters																Options			User Controls								
	Gain Max (dB) – Ear sim.	Max Out (dB SPL) – Ear sim.	Gain Max (dB) – 2cc	Max Out (dB SPL) – 2cc	Battery Size	ChannelFree™	Speech Cue Priority™	Frequency Composition™	Bandwidth (kHz)	Binaural Synchronization	Adaptive Directionality	True Directionality™	Automatic Directionality	Adaptive Noise Reduction Plus	Transient Noise Reduction	Reverb Reduction	Soft Noise Management	Wind Noise Monitor	Adap. Feedback Canceller Plus	Intelligent VC	Smart VC	Program Memories/Options	Environment Optimizer	Data Logging/Data Learning	Live Music/Cinema Programs	Comfort in Airplane Program	Thin Tube 0.9/1.3 mm	Telecoil/Auto Telephone	FM/DAI Adapter	Program Sel./Volume Control	Remote Control RC-N	Connectivity Accessories
<b>NEVARA 1</b>																																
<b>BTE</b>																																
NE1 CPx	77	137	71	132	13	●	●	-	8	●	-	-	-	■	-	-	■	-	●	-	-	7/4	-	●/-	-/-	-	●	●/●	o/o	●/●	o	-
NE1 P	72	138	68	134	13	●	●	-	8	●	-	-	●	■	-	-	■	-	●	-	-	7/4	-	●/-	-/-	-	●	●/●	o/o	●/●	o	-
NE1 N	55	128	49	122	312	●	●	-	8	●	-	-	●	■	-	-	■	-	●	-	-	6/4	-	●/-	-/-	-	●	-	-	●/● <sup>1</sup>	o	-
<b>RITE</b>																																
NE1 NR	73	132	64	123	312	●	●	-	8	●	-	-	●	■	-	-	■	-	●	-	-	6/4	-	●/-	-/-	-	●	-	-	●/● <sup>1</sup>	o	-
<b>ITE</b>																																
NE1 ITED	60	129	51	121	13	●	●	-	8	●	-	-	●	■	-	-	■	-	●	-	-	6/4	-	●/-	-/-	-	-	o/o	-	o/o <sup>1</sup>	o	-
NE1 ITCD	60	128	50	118	312	●	●	-	8	●	-	-	●	■	-	-	■	-	●	-	-	6/4	-	●/-	-/-	-	-	o/o	-	o/o <sup>1</sup>	o	-
NE1 ITC	60	128	50	118	312	●	●	-	8	-	-	-	-	■	-	-	■	-	●	-	-	6/4	-	●/-	-/-	-	-	o/o	-	o/o	-	-
NE1 CICP	57	125	47	116	10	●	●	-	8	-	-	-	-	■	-	-	■	-	●	-	-	5/4	-	●/-	-/-	-	-	-	-	o/o <sup>1</sup>	o	-
NE1 CICx	52	119	42	109	10	●	●	-	8	-	-	-	-	■	-	-	■	-	●	-	-	5/4	-	●/-	-/-	-	-	-	-	o/o <sup>1</sup>	o	-

### INIZIA 1

<b>INIZIA 1</b>																																
<b>BTE</b>																																
IN1 CPx	75	138	71	133	13	●	-	-	8	-	-	-	-	-	-	■	-	-	-	-	3/3	-	-/-	-	-	●	●/-	o/o	●/●	-	-	
IN1 CP	66	134	61	127	13	●	-	-	8	-	-	-	-	-	-	■	-	-	-	-	3/3	-	-/-	-	-	●	●/-	o/o	●/●	-	-	
IN1 N	55	127	50	121	312	●	-	-	8	-	-	-	-	-	-	■	-	-	-	-	3/3	-	-/-	-	-	●	-	-	●/-	-	-	
<b>RITE</b>																																
IN1 NR	73	132	63	123	312	●	-	-	8	-	-	-	-	-	-	■	-	-	-	-	3/3	-	-/-	-	-	●	-	-	●/-	-	-	
<b>ITE</b>																																
IN1 ITCD	56	123	46	113	312	●	-	-	8	-	-	-	-	-	-	■	-	-	-	-	3/3	-	-/-	-	-	-	o/-	-	o/o	-	-	
IN1 ITC	56	123	46	113	312	●	-	-	8	-	-	-	-	-	-	■	-	-	-	-	3/3	-	-/-	-	-	-	o/-	-	o/o	-	-	
IN1 CIC	49	118	39	109	10	●	-	-	8	-	-	-	-	-	-	■	-	-	-	-	1/3	-	-/-	-	-	-	-	-	-	-	-	

### SUPREMIA 7|3

<b>SUPREMIA 7 3</b>																																
<b>BTE</b>																																
SR7 SP	82	143	79	139	13	●	●	●	8	●	■	●	-	■	●	●	■	●	●	-	●	13/4	■	●/-	-/-	-	-	●/●	o/o	●/●	o	o
SR3 SP	82	143	79	139	13	●	●	●	8	-	■	-	-	■	-	-	■	-	●	●	-	11/4	-	●/-	-/-	-	-	●/●	o/o	●/●	o	o

<sup>1</sup> Program selector can be configured as a volume control

# GET CONNECTED ...



## REMOTE CONTROLS AND ACCESSORIES

<b>RC-N</b>	Volume Control +/-, Program Change, Mute
<b>SoundGate 3</b>	Same functionality as RC-N, Bluetooth® wireless audio reception, wired audio reception
<b>TV Adapter 2, Phone Adapter 2</b>	Wireless reception of TV audio (Bluetooth®) / wireless link to to landline phones (Bluetooth®)
<b>SoundGate Mic</b>	Wireless transmission of an interlocutor's voice

Since 1946, we have been passionate about developing quality hearing systems that enable people with hearing difficulties to enjoy authentic listening experiences. With Swiss Engineering, precision technology, and our commitment to individual service, we strive to exceed our customers' expectations. Our aim is to provide extra value to our partners every day. Bernafon representatives and employees in over 70 countries fulfill our vision to help people with impaired hearing communicate again without limitations.

**World Headquarters**

**Switzerland**

Bernafon AG  
Morgenstrasse 131  
3018 Bern  
Phone +41 31 998 15 15  
Fax +41 31 998 15 90

**SWISS**   
Engineering

**Bernafon Companies**

Australia · Canada · China · Denmark · Finland · France · Germany · Italy · Japan · Korea · Netherlands · New Zealand · Poland · Spain · Sweden · Switzerland · Turkey · UK · USA

[www.bernafon.com](http://www.bernafon.com)

**bernafon**   
Your hearing · Our passion